










finder®

SWITCH TO THE FUTURE

27 EVO

- ① RELÈ AD IMPULSI 10 A
- Ⓒ STEP RELAY 10 A
- Ⓕ TELERUPTEUR 10 A
- Ⓓ STROMSTOSS-SCHALTER 10 A
- Ⓝ IMPULSRELAIS 10 A
- Ⓔ RELE DE IMPULSOS 10 A
- Ⓟ RELÉ DE IMPULSO 10 A
- Ⓗ LÉPTETŐ (IMPULZUS) RELÉ 10 A
- ⒸZ SPÍNAČ IMPULSN OVLÁDANÝ KOMPAKTNÍ, 10 A
- ⓇO RELEE PAS CU PAS ELECTROMECHANICE 10 A



	U_N 230 V AC (50/60 Hz) $U_{min} - U_{max}$ - (0.8 - 1.1) U_N (50 Hz) - (0.85 - 1.1) U_N (60 Hz)
	27.21 1 NO (SPST-NO) 10 A 230 V AC 27.25 / 27.26 2 NO (DPST-NO) 10 A 230 V AC
	AC1 2300 VA AC15 (230 V AC) 500 VA
	 (230 V AC) 1000 W  (230 V AC) 360 W CFL - LED 200 W
	(-40...+40)°C
	15 (1mA)
IP20	

ⓘ Tipo 🇬🇧 Type 🇫 Types 🇩 Typ 🇳🇱 Type 🇪 Tipos 🇵 Tipo 🇭 Típus 🇨🇏 Typ 🇷🇴 Tipul	N° di impulsi Number of steps Nb. opérations Schaltvarianten Schakelposities N° impulsos N° de impulsos Kapcs. lépések száma Počet krok Numărul pașilor	Sequenze Sequences Sequences Schaltfolge Schakelprogramma Secuencias Seqüências Kapcsolási sorrend Postup krok Secvențele			
		1	2	3	4
27.21	2				
27.25	4				
27.26	3				

